

SIMATIC S7-300, Digital output SM 322, isolated, 8 DO (relay), 1x 40-pole, 24 V DC, 5 A or 230 V AC, 5 A, connectors with spring-loaded terminal can be used as of 6ES7392-1BM01-0AA0



Figure similar

Supply voltage	
Load voltage L+	
• Rated value (DC)	120 V
Load voltage L1	
• Rated value (AC)	230 V
Input current	
from supply voltage L+, max.	125 mA
from backplane bus 5 V DC, max.	40 mA
Power loss	
Power loss, typ.	3.2 W
Digital outputs	
Number of digital outputs	8; Relays
Switching capacity of the outputs	
• on lamp load, max.	1 500 W; 230 V AC
Output current	
• for signal "1" rated value	5 A

• for signal "1" minimum load current	5 mA
Switching frequency	
• with resistive load, max.	2 Hz
• with inductive load, max.	0.5 Hz
• on lamp load, max.	2 Hz
• mechanical, max.	10 Hz
Total current of the outputs (per group)	
horizontal installation	
— up to 60 °C, max.	5 A
vertical installation	
— up to 40 °C, max.	5 A
Relay outputs	
• Rated supply voltage of relay coil L+ (DC)	24 V
• Number of operating cycles, max.	300 000; 300 000 (24 V DC, at 2 A); 200 000 (120 V AC, at 3 A); 100 000 (230 V AC, at 3 A)
Switching capacity of contacts	
— with inductive load, max.	3 A; 3 A (230 V DC), 2 A (24 V AC)
— with resistive load, max.	8 A; 8 A (230 V DC), 5 A (24 V AC)
Cable length	
• shielded, max.	1 000 m
• unshielded, max.	600 m
Interrupts/diagnostics/status information	
Diagnostics function	No
Alarms	
• Diagnostic alarm	No
Diagnostic messages	
• Wire-break	No
• Short-circuit	No
• Fuse blown	No
• missing load voltage	No
Diagnostics indication LED	
• Rated load voltage PWR (green)	No
• Fuse OK FSG (green)	No
• Status indicator digital output (green)	Yes
Potential separation	
Potential separation digital outputs	
• between the channels	Yes
• between the channels, in groups of	1
• between the channels and backplane bus	Yes; Optocoupler
Isolation	
Isolation tested with	2000 V AC

Connection method	
required front connector	40-pin
Dimensions	
Width	40 mm
Height	125 mm
Depth	120 mm
Weights	
Weight, approx.	320 g
last modified:	08/30/2019